



SIZE OF CABINET 34" H X 28" W X 10" D FURNISHED BY CUSTOMER

REFER TO PAGE 1-11-26 (SIM-ESIG 4-4-5) FOR MIN. SERVICE DROP CLEARANCES

NOTES:

1. THIS CABINET SHALL BE FURNISHED AND INSTALLED BY CONTRACTOR WHEN THE NUMBER OF LOAD CONDUCTORS PER PHASE AT ONE SERVICE POINT EXCEED THE FOLLOWING:

CUSTOMER'S WIRE SIZE	NO. OF S.E. CONDUCTORS PER PHASE
3/0 AND SMALLER	4 (NORMALLY)
250 kcmil OR 4/0	3
350kcmil	2
500kcmil	2

2. THE CABINET WILL ACCOMODATE ONE TO FIVE SETS OF CUSTOMER'S LOAD WIRES AND FROM ONE TO THREE SINGLE OR THREE PHASE D.E. CO. SERVICE DROPS.

*3. ELECTRICAL GRADE COPPER OR ALUMINUM BUS ARE ACCEPTABLE AS CURRENT CARRYING CONDUCTORS.

*4. BRUSHING, BUFFING OR POLISHING PLATED ALUMINUM WILL REMOVE THE PROTECTIVE PLATE THUS CAUSING UNDUE OXIDATION OF THE ALUMINUM.

OVERHEAD SERVICE TERMINAL CABINET